

English

Quick Guide to Replacing the 2500W Lamp on a Solamagic S2 or S3

Required tools: Small Allen (hex) and TORX keys, a slot/flat-head screwdriver.

Don't touch the lamp with bare hands.

1. Take the device down from the wall or ceiling and place it on a table or workbench. It is virtually impossible to replace the lamp while the S2/S3 is still mounted.
2. Remove the cover caps on the left and right of the front side by removing the Allen bolts at the back.
3. Remove the polished aluminum trim strips at the ends of the grille by sliding them outwards.
4. Remove the grille.
5. Disconnect the lamp wires. For an S3, you will need to open the gray plastic junction box to do this.
6. Remove the bare metal partition next to the reflector and remove the rubber sealing rings (1x for the S2, 3x for the S3) around the connection cable.
7. Unscrew the reflector. *(Note during reassembly: the reflector is asymmetrical and therefore has a distinct left and right side).*
8. Take the reflector together with the lamp out of the housing, but pay close attention to the long wire behind the reflector. This wire runs through 1 or 2 guides. Gently pull the long wire through them without tearing them loose.
9. Clean the reflector if necessary and install the new lamp.
10. Reassemble everything by following these steps in reverse order.